

DOUBLE ANODE RECTIFYING TUBE

Double anode high vacuum rectifying tube

QUICK REFERENCE DATA

Transformer voltage	V_{tr}	2x350	V_{RMS}
D.C. current	I_o	90	mA



HEATING: Indirect by A.C.; parallel supply

Heater voltage	V_f	6.3	V
Heater current	I_f	600	mA

DIMENSIONS AND CONNECTIONS

Dimensions in mm

Base: Noval



OPERATING CHARACTERISTICS as two-phase half-wave rectifier

Transformer voltage	V_{tr}	2x250	2x275	2x300	2x350	V_{RMS}
D.C. output voltage	V_o	260	285	310	360	V
D.C. current	I_o	90	90	90	90	mA
Protecting resistance	R_t	2x125	2x175	2x215	2x300	Ω
Input capacitor of smoothing filter	C_{filt}	50	50	50	50	μF

LIMITING VALUES (Design centre rating system)

Transformer voltage	V_{tr}	max.	2x350	V_{RMS}	
D.C. current	I_o	max.	90	mA	
Cathode to heater voltage, peak, k pos	V_{kf_p}	max.	500	V	
Input capacitor of smoothing filter	C_{filt}	max.	50	μF	
Protecting resistance at transformer voltage	R_t min.	2x125	2x175	2x215	2x300 Ω
	V_{tr}	2x250	2x275	2x300	2x350 V_{RMS}

PHILIPS

Data handbook



Electronic
components
and materials

EZ80

page	sheet	date
1	1	1969.12
2	2	1969.01
3	FP	1999.03.19