

Specification MOSA/CV1085 Issue 6 Dated 26.II.1953 To be read in conjunction with K1001	<u>SECURITY</u>
	<u>Specification</u> Valve
UNCLASSIFIED	UNCLASSIFIED

→ Indicates a change

TYPE OF VALVE	- Cathode Ray Tube	<u>MARKING</u>
TYPE OF DEFLECTION	- Electrostatic: suitable for symmetrical operation	
BULB	- Internally coated with conductive coating	See K1001/4
SCREEN	- BYL 34	
PROTOTYPE	- VGR 85	

<u>RATINGS</u>		Note	<u>BASE</u>
			<u>CONNECTIONS</u>
Heater Voltage	(V)	4	Pin
Heater Current	(A)	1	Electrode
Max. Final Anode Voltage	(kV)	7	1 Cathode
Max. First Anode Voltage	(kV)	2	2 Grid
X-plate Sensitivity	(mm/V)	1345/Va3	3 Heater
Y-plate Sensitivity	(mm/V)	1300/Va3	4 Heater
			5 A ₁
			6 A ₂
			7 Internal Conductive Coating
			8 Y ₂
			9 X ₂
			10 A ₃
			11 X ₁
			12 Y ₁
<u>TYPICAL OPERATING CONDITIONS</u>			
Final Anode Voltage	(kV)	6	
Second Anode Voltage	(kV)	1.6	
First Anode Voltage	(kV)	1.8	
Beam Current	(μA)	20	
<u>DIMENSIONS</u>			
See drawings on page 4			

CV1085


TESTS

To be performed in addition to those applicable in K1001

Page 2

	Test Conditions					Test	Limits		No. Tested	Note
							Min.	Max.		
a	See K1001/5A.13					CAPACITANCES (pF)				
	(1) Each X or Y plate to all other electrodes					-	20	5%(10)		
	(2) Grid to all other electrodes					-	25			
	(3) One X to one Y plate					-	10			
b	Vh 4.0	Va 0	Va2 0	Va1 0	Vg 0	Ih (A)	0.8	1.3	100%	
c	4.0	6.0	Adjusted for optimum focus	1.8	Adjusted to give cut-off	Vg (V)	-30	-100	100%	
d	4.0	6.0	As in test (c)	1.8	-	(1) Vg (V) (2) Change in value of Vg from test (c)	-3	-	100%	
			Vg adjusted to give a light output of 0.02 candelas, through a C2 filter, on a close raster				-	60		
e	4.0	6.0	As in test (c)	1.8	As in (d) With sinusoidal deflecting voltages to give a 210mm. line at a frequency of 50 cps. and Duty Ratio = 1. Measurements to be made in X and Y deflection directions successively.	(1) Line width (mm) (2) Va2 (V)	-	1.3	100%	
							800	1800		
f	4.0	6.0	As in test (c)	1.8	-100	GRID INSULATION Grid Leakage Current (μ A) Increase in voltmeter reading	-	10	100%	
			Recommended method : See K1001/5A.3.2. Resistor = $10M\Omega$				-	100%	100%	
g	4.0	6.0	As in test (c)	1.8	Any convenient value	DEFLECTION SENSITIVITIES X-plate (mm/V) Y-plate (mm/V)	1090 Va3	1660 Va3	5% (10)	
							1000 Va3	1600 Va3		
h	4.0	6.0	As in test (c)	1.8	Any convenient value	Deviation of spot from centre of screen (mm)	-	25	100%	

	Test Conditions					Test	Limits		No. Tested	Note
							Min.	Max.		
j	Vh 4.0	Va (kV) 6.0	Va2 As in test (c)	Val (kV) 1.8	Vg Any con- ven- ient value	USEFUL SCREEN AREA Deflections measured from centre of screen	X-deflection (mm) ±105	-	100%	
k	4.0	6.0	As in test (c)	1.8	Any con- ven- ient value	Orientation of Y axis of deflection Angles measured relative to axis 00° in drawing on page 4	-	±10°	100%	
l	4.0	6.0	As in test (c)	1.8	Any con- ven- ient value	Angle between X and Y axes of deflection	85°	95°	5%(10)	
m	4	6	As in test (c)	1.8	Any con- ven- ient value	The screen shall not be worse for graininess than a standard pattern Deflection voltages to give a raster covering the useful screen area. The spot shall be de- focussed such that separate lines shall not be discernible on the raster.			100%	
n	4	6	As in test (c)	1.8	-	LIFE HOURS At the end of 1000 hours the tube shall meet the specification requirements Normal brightness and con- tinuous spot movement over a raster of size 210 x 100 mm.			1%	
o	Tests to be performed using Test Set 331, with a close raster of convenient size.					AFTERCLOW (seconds) N ₃ Filter N ₄ Filter	20	30		



VIEW OF UNDERSIDE OF BASE.

295 MAX.
285 MIN. DIA.

235 DIA. SCREEN.

63 MAX.
50 MIN.

280 R.

215 MAX.
218 MIN.

650 ± 10

322 R.

222 MIN.

73 MAX.
NECK DIA. 60 MIN. OVER
THIS LENGTH.

NOTES

1. THE INTERNAL CONDUCTIVE COATING SHALL BE OF SUCH DIMENSIONS THAT IT FUNCTIONS EFFECTIVELY BUT DOES NOT OBSCURE THE REQUIRED USEFUL SCREEN AREA.
2. WHEN VIEWING THE SCREEN WITH THE TUBE POSITIONED SO THAT THE BASE SPIGOT IS UPPERMOST, A POSITIVE VOLTAGE APPLIED TO THE TERMINAL X₁ SHALL DEFLECT THE SPOT TO THE RIGHT AND A POSITIVE VOLTAGE APPLIED TO THE TERMINAL Y₁ SHALL DEFLECT THE SPOT DOWNWARDS.

ALL DIMENSIONS IN MILLIMETRES.