

B9A Base

Current Equipment Type

TYPE ECF82
MINIATURE
TRIODE PENTODE
FREQUENCY CHANGER



The BRIMAR ECF82 is a triode-pentode frequency changer featuring a high slope triode and a high input impedance pentode of high slope suitable for use in television receivers for Band III. The high input impedance at 200 Mc/s permits a sensibly constant conversion gain to be obtained over Bands I and III. The low value of C_{ag} for the pentode and C_{ap} , at facilitate the reduction of oscillator radiation. The use of low oscillator grid current to obtain the required heterodyne voltage reduces the frequency drift of the oscillator to a minimum.

Heater Current	0.45 amp.
Heater Voltage	6.3 volts (nom.)

RATINGS

Heater—Cathode Potential (cathode positive)	220 volts max.
Heater—Cathode Potential (cathode negative)	90 volts max.
											<i>Triode</i>
Anode Voltage ($I_a = 0$)	550
Anode Voltage	300
Screen (g_2) Voltage	—
Anode Dissipation	2.7
Screen Dissipation	—
Positive D.C. Grid No. 1 Voltage	0
Cathode Current	20
Grid Resistance	1
											<i>Pentode</i>
											550 volts max.
											300 volts max.
											300 volts max.
											2.8 watts max.
											0.5 watts max.
											0 volts max.
											20 mA max.
											1 megohm max.

CHARACTERISTICS

Anode Voltage	<i>Triode</i>	<i>Pentode</i>
Screen Voltage	150	250 volts
Cathode Bias Resistor	—	110 volts
Anode Current	56	68 ohms
Screen Current	18	10 mA
Mutual Conductance	—	3.5 mA
Anode Impedance (approx.)	8.5	5.2 mA/V
Amplification Factor	5	400 k ohms
Grid No. 1 Voltage (for $I_a = 10 \mu A$)	40	—
											—12	—10 volts

TYPICAL OPERATION AS MIXER

											<i>Triode</i>	<i>Pentode</i>
Anode Voltage	100	170
Screen Voltage	110	170 volts
Cathode Bias Resistor	0	680 ohms
Grid Leak Resistor	27	100 k ohms
Anode Current	7.0	6.6 mA
Screen Current	—	2.5 mA
Heterodyne Voltage	—	3.0
Conversion Conductance	—	1.6
												5.0 volts peak
												1.65 mA/V

INTER-ELECTRODE CAPACITANCES *

Pentode Grid No. 1 to Pentode Anode	0.006 pF
Pentode Input	5.0 pF
Pentode Output	3.5 pF
Triode Grid to Triode Anode	1.8 pF
Triode Grid to Cathode	2.5 pF
Triode Anode to Cathode	1.0 pF
Cathode to Heater (either section) approx.	3.0 pF

* Measured with external shield.

Type ECF82 is a commercial equivalent of the CV5063.

