




# 6X5G/GT



6X5G.

Replacement Types

## TYPES 6X5G, 6X5GT (OCTAL BASE)



6X5GT.

### FULL-WAVE RECTIFIERS

The BRIMAR types 6X5G, 6X5GT are indirectly heated full-wave rectifiers for use in equipment where the current drain does not exceed 70 mA.

#### RATINGS

Heater Voltage	...	...	...	...	...	...	...	...	6.3 volts
Heater Current	...	...	...	...	...	...	...	...	0.6 amp.
Peak Inverse Voltage	...	...	...	...	...	...	...	...	1,250 volts max.
Peak Current (Each Anode)	...	...	...	...	...	...	...	...	210 mA max.
Heater Cathode Potential	...	...	...	...	...	...	...	...	450 volts max.

#### CHARACTERISTICS AS FULL-WAVE RECTIFIER

##### CONDENSER INPUT

R.M.S. Input per Anode	...	...	...	...	...	...	...	...	325 volts max.
Supply Impedance per Anode	...	...	...	...	...	...	...	...	150 ohms min.
Rectified Current	...	...	...	...	...	...	...	...	70 mA max.
Reservoir Condenser	...	...	...	...	...	...	...	...	32 $\mu$ F max.

