



T.				U_f	I_f	U_a	U_{g2}	U_{g1}	I_a	I_{g2}	S	R_i	μ
				V	A	V	V	V	mA	mA	mA/V	k Ω	
12 Б 1 М	A+A+L	CCCP	1	12,5	0,22	25	25	-1	1,1	0,4	1,9	7,5	
12 Б 2 М	A+A+F	CCCP	2	12,5	0,15	25	25	-1	1,3	0,3	0,8	150	
12 Ж 1 М	F	CCCP	3	12,5	0,225	25	25	-1,5	2	0,5	1,4	200	
12 К 1 М	Fv-mu	CCCP	3	12,5	0,225								
12 М 1 М	C+L	CCCP	4	12,5	0,225	25	25	-1	1,1	0,3	1,9	7,5	
12 SW 7 ¹⁾	A+A+C	RCA	—	12,6	0,15	26,5	($R_g = 2M\Omega$)		1,1	—	1,1	15,5	

¹⁾ vide gr. 294

