





T.			U <sub>f</sub>	I <sub>f</sub>	Cl.	U <sub>a</sub>	U <sub>g2</sub>	U <sub>g3</sub>	U <sub>g1</sub>	I <sub>a</sub>	I <sub>g2</sub>	I <sub>g1</sub>	U <sub>g1</sub> ≈	P <sub>dr</sub>	R <sub>o/a</sub>	P <sub>o</sub>		P <sub>g2</sub>		P <sub>a</sub>												
																V	W	W	W													
PE 1/100			V	A	Cl.	V	V	V	V	mA	mA	mA	V	W	kΩ	W	W	W	W	W												
																					600	250	0	-100	205	28	7,5	124	0,84	78	7	45
																					800	250	0	-110	190	28	6	134	0,73	107	7	45
																					1000	250	0	-120	177	28	5	144	0,65	132	7	45
																					600	250	0	-120	120	23	6,5	150	0,9	51	5,8	21
																					800	250	0	-120	120	23	6,5	150	0,9	75	5,8	21
																					1000	150	-100	-100	72	24	10	140	1,3	27	3,6	45
																					600	250	0	-30,5	114	7,5	8	26,5	0,38	23,4	1,9	45
																					800	250	0	-33	85	6	4	22,5	0,17	23	1,5	45
																					1000	250	0	-34	68	4,5	2	20,5	0,08	23	1,15	45
600	250	0	-33	(28 ÷ 102) × 2	(11 ÷ 28) × 2	0	33 × 2	0	6,32	7 × 2	20,2 × 2																					
800	250	0	-33,5	(28 ÷ 108) × 2	(8 ÷ 27) × 2	0	34 × 2	0	7,56	6,8 × 2	31,4 × 2																					
1000	250	0	-34	(26 ÷ 134) × 2	(5 ÷ 28) × 2	0,8 × 2	42 × 2	0,03 × 2	8,8	7 × 2	37 × 2																					
				40																												
				1000	300																45											

S = 6 mA/V;  $\mu_{(g^2/g^1)} = 6,7$   
 maximum I<sub>k</sub> = 240 mA; P<sub>g1</sub> = 0,5 W

$C_{g1}$	$C_a$	$C_{g1/a}$
pF	pF	pF
22,5	11	0,1

Equivalents

OS 51	Tu
6083	amer
9909	Amp

